

Revised 4/1/12

1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39

**[Joint Utilities October 19, 2012 Proposed Changes]**

**New York State  
Standardized Interconnection Requirements and Application Process  
for New Distributed Generators 2 MW or Less Connected in Parallel with Utility  
Distribution Systems**



**New York State  
Public Service Commission**

**April 2012**

**Table of Contents**

1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34

Section I. Application Process.....

    A. Introduction.....

    B. Application Process Steps for Inverter Based Systems 25 kW or Less

    C. Application Process Steps for Non-Inverter Based Systems .....

        and Inverter Based Systems above 25 kW up to 2 MW.....

    D. Web-Based Standard Interconnection Requirements.....

Section II. Interconnection Requirements.....

    A. Design Requirements.....

        1. Common.....

        2. Synchronous Generators.....

        3. Induction Generators.....

        4. Inverters.....

        5. Minimum Protective Function Requirements.....

        6. Metering.....

    B. Operating Requirements.....

    C. Dedicated Transformer.....

    D. Disconnect Switch.....

    E. Power Quality.....

    F. Power Factor.....

    G. Islanding.....

    H. Equipment Certification.....

    I. Verification Testing.....

    J. Interconnection Inventory.....

Section III. Glossary of Terms.....

Appendices

    A. Standardized Contract

    B. Standardized Application for Inverter Based Systems

    C. Standardized Application for Non-Inverter Based Systems

    D. Cost Responsibility for Dedicated Transformers and Other Safety Equipment

---

Table of Contents ..... 1

**Table of Contents**

Section I. Application Process .....1

- A. Introduction.....1
- B. Application Process Steps for Systems 25 kW or Less .....2
- C. Application Process Steps for Systems above 25 kW up to 2 MW .....4
- D. Web-Based Standard Interconnection Requirements.....10

Section II. Interconnection Requirements.....11

- A. Design Requirements .....11
  - 1. Common.....11
  - 2. Synchronous Generators .....12
  - 3. Induction Generators.....13
  - 4. Inverters .....13
  - 5. Minimum Protective Functions.....14
  - 6. Metering.....15
- B. Operating Requirements .....17
- C. Dedicated Transformer .....18
- D. Disconnect Switch .....18
- E. Power Quality .....19
- F. Power Factor .....19
- G. Islanding.....20
- H. Equipment Certification.....20
- I. Verification Testing .....21
- J. Interconnection Inventory .....21

Section III. Glossary of Terms.....22

Appendices

- A. Standardized Contract.....26
- B. Standardized Application for Systems 25 kW or Less .....33
- C. Standardized Application for Systems above 25 kW up to 2 MW .....35

1 **Section I. Application Process**

2  
3 **New York State**  
4 **Standardized Interconnection Requirements and Application Process for New**  
5 **Distributed Generators 2 MW or Less Connected in Parallel with Utility**  
6 **Distribution Systems**  
7

8 **A. Introduction**  
9

10 This section provides a framework for processing applications to:

- 11
- 12 | • interconnect new distributed generation (“DG”) facilities with a nameplate rating  
13 | of 2 MW or less [aggregated on the customer side of the point of common  
14 | coupling (“PCC”)]~~L.H.~~; and
  
  - 15 | • review any modifications affecting the interface at the PCC to existing  
16 | ~~DG distributed generation~~ facilities with a nameplate rating of 2 MW or less  
17 | (aggregated on the customer side of the PCC) that have been interconnected to the  
18 | utility distribution system and where an existing contract between the applicant  
19 | and the utility is in place.  
20

21 Generation neither designed to operate, nor operating, in parallel with the utility’s  
22 electrical system is not subject to these requirements. This section will ensure that  
23 applicants are aware of the technical interconnection requirements and utility  
24 interconnection policies and practices. This section will also provide applicants with an  
25 understanding of the process and information required to allow utilities to review and  
26 accept the applicants’ equipment for interconnection in a reasonable and expeditious  
27 manner.

28  
29 The time required to complete the process will reflect the complexity of the proposed  
30 project. Projects using previously submitted designs certified per the requirements of  
31 Section II.H will move through the process more quickly, and several steps may be  
32 satisfied with an initial application depending on the detail and completeness of the  
33 application and supporting documentation submitted by the applicant. Applicants  
34 submitting systems utilizing certified equipment however, are not exempt from providing  
35 utilities with complete design packages necessary for the utilities to verify the electrical  
36 characteristics of the generator systems, the interconnecting facilities, and the impacts of  
37 the applicants’ equipment on the utilities’ systems.  
38

39 The application process and the attendant services must be offered on a non-  
40 discriminatory basis. The utilities must clearly identify their costs related to the  
41 applicants’ interconnections, specifically those costs the utilities would not have incurred

1 but for the applicants' interconnections. The utilities will keep a log of all applications,  
2 milestones met, and justifications for application-specific requirements. The applicants  
3 are to be responsible for payment of the utilities' costs, as provided for herein.

4  
5 All application timelines shall commence the next Business Day following receipt of  
6 information from the applicant.

7  
8 Staff of the Department of Public Service ("~~DPS (Staff)~~") will monitor the application  
9 process to ensure that applications are addressed in a timely manner. To perform this  
10 monitoring function, DPS Staff will meet periodically with utility and applicant  
11 representatives.

12  
13 A glossary of terms used herein is provided in Section III.

14  
15 **B. Application Process Steps for Inverter Based Systems 25 kW or Less**

16  
17 Exception: For inverter based systems above 25 kW up to 300 kW, applicants may  
18 follow the expedited application process outlined in this section provided that the inverter  
19 based system has been certified and tested in accordance with the most recent revision of  
20 UL 1741 and the utility has approved the project accordingly. The utility has fifteen (15)  
21 Business Days upon receipt of the original application submittal to determine and notify  
22 the applicant in writing of its findings upon review of the application. If the utility  
23 determines that an inverter based system is not eligible for the fast track or expedited  
24 application process, the applicant can:

25  
26 1) Proceed with the remaining steps of Section I.C of the SIR (Non-Inverter Based  
27 Systems or Inverter Based Systems above 25 kW up to 2 MW); or

28  
29 2) Request a review by DPS Staff.

30  
31 **STEP 1: Initial Communication from the Potential Applicant**

32  
33 Communication could range from a general inquiry to a completed application.

34  
35 **STEP 2: The Inquiry is Reviewed by the Utility to Determine the Nature of the**  
36 **Project**

37  
38 Technical staff from the utility discusses the scope of the interconnection with the  
39 potential applicant (either by phone or in person) to determine what specific information  
40 and documents (such as an application, contract, technical requirements, specifications,  
41 listing of qualified type-tested equipment/systems, applicable rate schedules, and  
42 metering requirements) will be provided to the potential applicant. The preliminary  
43 technical feasibility of the project at the proposed location may also be discussed at this

1 | time. All such information and a link to the DG portion of the utility’s website or a copy  
2 | of the New York State Standardized Interconnection Requirements and Application  
3 | Process for New Distributed Generators 2 MW or Less Connected in Parallel with Utility  
4 | Distribution Systems (“Standardized Interconnection Requirements” or “standardized  
5 | interconnection requirements (SIR)” and any utility-specific documents) must be  
6 | provided sent to the applicant within three (3) Business Days~~business days~~ following the  
7 | initial communication from the potential applicant, unless the potential applicant  
8 | indicates otherwise. A utility representative will be designated to serve as the single  
9 | point of contact for the applicant (unless the utility informs the applicant otherwise) in  
10 | coordinating the potential applicant’s project with the utility.

### 11 | **STEP 3: Potential Applicant Files an Application**

12 | **STEP 3: Potential Applicant Files an Application**

13 |

14 | The potential applicant submits an application package to the utility. No application fee  
15 | is required of the applicant for systems 25 kW or less. A complete application package  
16 | will consist of (1) a letter of authorization by the customer (if the applicant is an agent for  
17 | the customer), (2) the standard single page application form completed and signed by the  
18 | applicant, (3) a signed copy of the standardized contract, (4) a three line diagram for the  
19 | system identifying the manufacturer and model number of the equipment,~~(s)~~, (5) a copy  
20 | of the manufacturer’s data sheet~~(s)~~ for the power generating equipment and  
21 | interconnection equipment,~~(s)~~; (6) a copy of the ~~manufacturers~~ verification test  
22 | procedure~~(s)~~ to be performed or, at the utility’s option, and (7) a copy of the standardized  
23 | verification test procedure (made available to the applicant by the utility) and (7) if not  
24 | listed in the Department of Public Service Certified Interconnection Equipment found on  
25 | the Commission’s website, a copy of the equipment~~equipment~~(s) certification(s) to the  
26 | most recent~~UL 1741 (November 2005~~ revision of UL 1741 entitled “Inverters,  
27 | Converters, Controllers and Interconnection Safety Equipment for Use with Distributed  
28 | Energy Resources” if ) if applicable. The proposed equipment(s) will be considered  
29 | acceptable by the utility if ~~meeting they meet~~ the requirements of Section II.H herein.— If  
30 | the applicant’s application is deemed not complete by the utility, ~~then~~ within five (5)  
31 | Business Days~~business days~~ of receipt of the application package the utility will notify  
32 | the applicant by email, fax, or other form of written communication, and explain the  
33 | deficiencies. If the applicant’s proposed system meets the SIR technical requirements the  
34 | utility will return a signed and executed New York State Standardized  
35 | Contract~~standardized contract~~ to the applicant within ten (10) Business Days~~business~~  
36 | days of receipt of~~receiving~~ the application and the applicant may proceed with the  
37 | proposed installation. If the proposed system does not meet the SIR technical  
38 | requirements, ~~then~~ the utility will so notify the applicant within ten (10) Business  
39 | Days~~business days~~ of receipt of~~receiving~~ the application by email, fax, or other form of  
40 | written communication and explain the technical issues or problems.

41 |

42 | Applicants will be placed in each utility’s interconnection inventory upon receipt of a  
43 | completed application and execution of the New York State Standardized Interconnection

Contract by the utility. If the final acceptance as set out in Step 6 below is not completed within twelve (12) months of receipt of such executed copy of the New York State Standardized Contract as a result of applicant inactivity, the utility has the right to notify the applicant by U.S. first class mail that the applicant's project will be removed from the utility's interconnection inventory if the applicant does not respond within fifteen (15) Business Days of the issue of such notification.

With respect to an applicant proposing to install a system rated 25 kW or less-, that is to be net-metered, if the utility determines that it is necessary to install a dedicated transformer(s) or other equipment to protect the safety and adequacy of electric service provided to other customers, the applicant shall be informed of its responsibility for the actual costs for installing the dedicated transformer(s) and other safety equipment. ~~Appendix D sets forth the~~ The following tables reflect the maximum responsibility each applicant shall have with respect to the actual cost of the dedicated transformer(s) and other safety equipment.

~~Maximum Expense for Dedicated Transformer and Other Safety Equipment for Residential Net Metered Customers (25 kW or Less)~~

<del>Generator Type</del>	<del>Generator Size</del>	<del>Maximum Equipment Cost to Customer</del>
<del>Micro CHP / Fuel Cell</del>	<del>Less than or equal to 10 kW</del>	<del>\$350</del>
<del>Solar</del>	<del>Less than or equal to 25 kW</del>	<del>\$350</del>
<del>Micro hydroelectric</del>	<del>Less than or equal to 25 kW</del>	<del>\$350</del>
<del>Wind</del>	<del>Less than or equal to 25 kW</del>	<del>\$750</del>

~~Maximum Expense for Dedicated Transformer and Other Safety Equipment for Non-Residential Net Metered Customers (25 kW or Less)~~

<del>Generator Type</del>	<del>Generator Size</del>	<del>Maximum Equipment Cost to Customer</del>
<del>Fuel Cell</del>	<del>Less than or equal to 25 kW</del>	<del>As determined by Utility</del>
<del>Solar</del>	<del>Less than or equal to 25 kW</del>	<del>\$350</del>
<del>Micro hydroelectric</del>	<del>Less than or equal to 25 kW</del>	<del>As determined by Utility</del>
<del>Wind</del>	<del>Less than or equal to 25 kW</del>	<del>\$750</del>

**STEP 4: System Installation**

The applicant will install the DG system according to the utility accepted design and the equipment manufacturer's requirements. If there are any design variations from the originally approved three line diagram, a revised three line diagram shall be submitted by

1 the applicant for the utility's review and acceptance. All inverter based systems will be  
2 allowed to interconnect to the utility system for a period not to exceed two hours prior to  
3 issue of the utility's final acceptance in Step 6 below, for the sole purpose of assuring  
4 proper operation of the installed equipment.

5  
6 The utility also reserves the right to require a copy of the electrical inspection certificate  
7 be provided by the applicant. Upon the utility's receipt of application of a notification of  
8 system completion and, if so requested by the utility, receipt of the electrical inspection  
9 certificate, the utility will review the submitted final installation documentation to ensure  
10 the system is ready for verification testing and advise the applicant of its findings within  
11 (5) Business Days.

12  
13 ~~For net metered systems as defined in Section H.A.6, any modifications related to~~  
14 ~~existing metering configurations to allow for net metering shall be completed by the~~  
15 ~~utility prior to Step 5. The utility shall complete the necessary metering changes within~~  
16 ~~ten (10) business days of receiving request from the applicant.~~

#### 19 **STEP 5: The Applicant's Facility is Tested in Accordance with the Standardized** 20 **Interconnection Requirements.**

21  
22 Verification testing will be performed by the applicant in accordance with the written  
23 verification test procedure(s). ~~provided by the equipment manufacturer.~~ The verification  
24 testing will be conducted within ten (10) ~~business days~~ Business Days of ~~the utility's~~  
25 ~~review of the applicant's final system~~ installation documentation at a mutually agreeable  
26 time, and the utility shall be given the opportunity to witness the tests. ~~The~~ ~~If the utility~~  
27 ~~opts not to witness the test, the~~ applicant will send the utility within five (5) Business  
28 Days of ~~completion of such tests~~ the test a written notification, certifying that the  
29 system has been installed and tested in compliance with the SIR, the utility-accepted  
30 design and the written verification test procedure(s), subject to the utility's acceptance as  
31 described below. ~~equipment manufacturer's instructions.~~ ~~The applicant's facility will be~~  
32 ~~allowed to commence parallel operation upon satisfactory completion of the tests in Step~~  
33 ~~5. The applicant must have complied with and must continue to comply with all~~  
34 ~~contractual and technical requirements.~~

35  
36 ~~Within five (5) Business Days of receipt of the applicant's written certification of the~~  
37 ~~verification tests, the utility will either notify the applicant that the verification test results~~  
38 ~~are acceptable and any necessary metering changes by the utility will be scheduled or, in~~  
39 ~~the event that the utility cannot accept the verification test results as presented, the utility~~  
40 ~~will request that the applicant and the utility set a date and time for the applicant to re-~~  
41 ~~perform the verification tests in order to allow the utility to witness the conduct of the~~  
42 ~~verification tests and the operation of the DG system. This witnessed verification testing~~  
43 ~~must be completed within ten (10) Business Days of the request. Within five (5)~~

1 Business Days of the completion of any such testing, if the utility remains unable to  
2 accept the verification test results the utility shall provide the applicant a detailed  
3 explanation of the deficiencies of the DG system.

4 -  
5 The utility shall complete any necessary metering changes within ten (10) Business Days  
6 of the utility accepting the verification test results for the DG system.

7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25 **STEP 6: Final Acceptance**

26  
27 Within five (5) Business Days of the completion of any necessary metering  
28 changes~~business days of receiving the written test notification from Step 5,~~ the utility will  
29 ~~either~~ issue to the applicant a formal letter of acceptance for interconnection. The  
30 applicant's DG system, or will be allowed to commence parallel operation only upon  
31 receipt of a formal letter of acceptance of the interconnection from the utility. The  
32 receipt of such formal letter of acceptance does not relieve~~request that~~ the applicant from  
33 continuing to comply with all contractual and technical requirements~~utility set a date and~~  
34 the time for an on-site verification and witness operation of the system.~~This joint on-site~~  
35 ~~verification must be completed within ten (10) business days after being requested.~~  
36 Within five (5) business days of the completion of the on-site verification, the utility will  
37 issue to the applicant shall abide by such requirements as long as the DG system is  
38 interconnected to the utility's system~~either a formal letter of acceptance for~~  
39 ~~interconnection or a detailed explanation of the deficiencies in the system.~~

40  
41 **C. Application Process Steps for Non-Inverter Based Systems and Inverter Based**  
42 **Systems above 25 kWKW up to 2 MW**

1 **Exception:** For inverter based systems above 25 kW up to 300 kW certified and tested in  
2 accordance with the most recent revision of UL 1741~~200 kW~~, applicants and utilities are  
3 encouraged to use ~~may follow~~ the expedited application process (~~outlined under~~ Section  
4 I. B.) ~~of the SIR, as long as the inverter based system has been certified and tested in~~  
5 ~~accordance with UL 1741 (November 2005 revision) and the utility has approved the~~  
6 ~~project accordingly. The utility has fifteen (15) business days from original application~~  
7 ~~submittal to determine and notify the applicant in writing of its findings. If the utility~~  
8 ~~determines that the inverter based system is not eligible for the fast track or expedited~~  
9 ~~application process, the applicant can:~~

10 1) ~~Proceed with the remaining steps of Section I.C of the SIR (Systems above 25 kW~~  
11 ~~up to 2 MW); or~~

12  
13 2) ~~Request a review by the Department of Public Service.~~

14  
15 ~~For non inverter based systems and those inverter based systems not certified and tested~~  
16 ~~in accordance with UL 1741 above 25 kW up to 200 kW, the potential applicants and~~  
17 ~~utilities are encouraged to use expedited application process (Section I. B.), but only in~~  
18 ~~circumstances where the utility deems it to be appropriate.~~

19  
20 **STEP 1: Initial Communication from the Potential Applicant.**

21  
22 Communication could range from a general inquiry to a completed application.

23  
24 **STEP 2: The Inquiry is Reviewed by the Utility to Determine the Nature of the**  
25 **Project.**

26  
27 Technical staff from the utility discusses the scope of the interconnection with the  
28 potential applicant (either by phone or in person) to determine what specific information  
29 and documents (such as an application, contract, technical requirements, specifications,  
30 listing of qualified type-tested equipment/systems, application fee information, applicable  
31 rate schedules, and metering requirements) will be provided to the potential applicant.  
32 The preliminary technical feasibility of the project at the proposed location may also be  
33 discussed at this time. All such information and a link to the distributed generation  
34 portion of the utility's website or a copy of the SIR and any utility-specific  
35 documents~~standardized interconnection requirements~~ must be provided~~sent~~ to the  
36 applicant within three (3) Business Days~~business days~~ following the initial  
37 communication from the potential applicant, unless the potential applicant indicates  
38 otherwise. A utility representative will be designated to serve as the single point of  
39 contact for the applicant (unless the utility informs the applicant otherwise) in  
40 coordinating the potential applicant's project with the utility.

41  
42 **STEP 3: Potential Applicant Files an Application.**

1 The potential applicant submits an application to the utility. The submittal must include  
2 the completed standard application form, including a copy of equipment certification to  
3 the most recent UL-1741 (November 2005 revision of UL 1741) as applicable, a three line  
4 diagram specific to the proposed system, a letter of authorization (if applicant is agent for  
5 the customer), and payment of a non-refundable \$350 application fee, except that the  
6 application fee shall be refunded to net metering customer-generators unless applied  
7 toward the cost of installing a dedicated transformer (s) or other safety equipment. No  
8 application fee is required of the applicant for systems 25 kW or less.- If the applicant  
9 proceeds with the project to completion, the application fee will be applied as a payment  
10 to the utility's total cost for interconnection, including the cost of processing the  
11 application. Within five (5) Business Days~~business days~~ of receiving the application, the  
12 utility will notify the applicant of receipt and whether the application has been completed  
13 adequately. It is in the best interest of the applicant to provide the utility with all  
14 pertinent technical information as early as possible in the process. If the required  
15 documentation is presented in this step, it will allow the utility to perform the required  
16 reviews and allow the process to proceed as expeditiously as possible.

17 Applicants will be placed in the utility's interconnection inventory upon receipt of the  
18 applicant's completed application, including receipt of the application fee. If either of the  
19 milestones identified below are not met due to customer inactivity, the utility has the  
20 right to notify the customer by U.S. first class mail that the customer's project will be  
21 removed from the utility's interconnection inventory if the customer does not respond  
22 within fifteen (15) Business Days of the issue of such notification. If there is no status  
23 update provided by the customer in response to the mailed notification, the utility may  
24 proceed to remove the application from the inventory.

- 25 • Applicant commits to utility construction of utility's system modifications within  
26 twelve (12) months of filing an application; or
- 27 • Final acceptance and utility cost reconciliation occurs within eighteen (18)  
28 months of filing an application.

29 The utility will refund any advance payments for services or construction not yet  
30 completed should the applicant be removed from the utility's interconnection inventory.  
31 If the costs incurred by the utility exceed the advance payments made by the applicant  
32 prior to removal from the interconnection inventory, the applicant will receive a bill for  
33 any balance due to the utility.

34  
35 **STEP 4: Utility Conducts a Preliminary Review and Develops a Cost Estimate**  
36 **for the Coordinated Electric System Interconnection Review (CESIR).**  
37

38 The utility conducts a preliminary review of the proposed system interconnection. Upon  
39 completion of the preliminary review, the utility will inform the applicant as to whether  
40 the proposed interconnection is viable or not, and provide the applicant with an estimate  
41 of costs associated with the completion of the CESIR. The preliminary review shall be

1 completed and a written response detailing the outcome of the preliminary review shall  
2 be sent to the applicant within fifteen (15) ~~Business Days~~business days of the completion  
3 of Step 3.— The utility's response to those applicants proposing to interconnect non-  
4 inverter based DG systems, aggregate inverter based DG systems above 25 kW and up to  
5 2 MW, or proposing to interconnect to network systems will include preliminary  
6 comments on requirements for safety equipment, protective relaying, metering and  
7 telemetry.

8  
9 **STEP 5: Applicant Commits to the Completion of the CESIR**

10  
11 Prior to commencement of the CESIR, the applicant shall provide the following  
12 information to the utility:

- 13  
14  
15  
16  
17  
18  
19  
20  
21
- a complete detailed interconnection design package
  - the name and phone number, and agent letter of authorization (if appropriate) of the individual(s) responsible for addressing technical and contractual questions regarding the proposed system, and
  - if applicable, ~~advance~~advanced payment of the costs associated with the completion of the CESIR.

22 The complete detailed interconnection design package shall include:

- 23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40
- (1) Electrical schematic drawing(s) reflecting the complete proposed system design which are easily interpreted and of a quality necessary for ~~a~~ full interconnection. The drawings shall show all electrical components proposed for the installation, and their connections to the existing on-site electrical system from that point to the PCC.
  - (2) A complete listing of all interconnection devices proposed for use at the PCC. A set of specifications for this equipment shall be provided by the applicant upon request from the utility.
  - (3) The written verification test procedure provided by the equipment manufacturer, if such procedure is required by this document. For non-inverter based systems, testing equipment must be capable of measuring that protection settings operate within the

1 | appropriate times and thresholds set forth in Section  
2 | II.

3 |  
4 | (4)- Three (3) copies of the following information:  
5 |

- 6 | • Proposed three line diagram of the generation system showing the  
7 | interconnection of major electrical components within the system.  
8 | Proposed equipment ratings clearly ~~need~~needs to indicate:  
9 |

10 | 1) Number, individual ratings, and type of units comprising the  
11 | above rating;

12 | 2) General high voltage bus configuration and relay functions; and

13 | 3) Proposed generator step-up transformer MVA ratings,  
14 | impedances, tap settings and winding voltage ratings;

- 15 | • Electrical studies as requested by the utility to demonstrate that the  
16 | design is within acceptable limits, inclusive and limited to the  
17 | following: system fault, relay coordination, flicker, voltage drop,  
18 | and harmonics. This shall include all relay, communication, and  
19 | controller set points.  
20 |

#### 21 | **STEP- 6: Utility Completes the CESIR**

22 |  
23 | The CESIR will consist of two parts:  
24 |

- 25 | (1) a review of the impacts to the utility system associated  
26 | with the interconnection of the proposed system, and  
27 |  
28 | (2) a review of the proposed system's compliance with the  
29 | applicable criteria set forth below.  
30 |

31 | A CESIR will be performed by the utility to determine if the proposed generation on the  
32 | circuit results in any relay coordination, fault current, and/or voltage regulation problems.  
33 | A full CESIR may not be needed if the aggregate generation is less than (1)÷ 50 kW on a  
34 | single-phase branch of a radial distribution circuit; or (2) 150 kW on a single distribution  
35 | feeder.  
36 |

37 | In addition, at the option of the utility and based on each utility's specific technical  
38 | requirements, a CESIR may be required for DG systems that are being proposed on the  
39 | utility's network systems.  
40 |

1 | The CESIR shall be completed within sixty (60) ~~Business Days~~<sup>business days</sup> of receipt  
2 | of the information set forth in Step 5. For systems utilizing type-tested equipment, the  
3 | time required to complete the CESIR may be reduced.

4 |  
5 | Upon completion of the CESIR, the utility will provide the following, in writing, to the  
6 | applicant:

- 7 |  
8 |           (1) utility system impacts, if any;  
9 |  
10 |           (2) notification of whether the proposed system meets the  
11 |           applicable criteria considered in the CESIR process;  
12 |  
13 |           (3) if applicable, a description of where the proposed  
14 |           system is not in compliance with these requirements;  
15 |  
16 |           (4) ~~Subject to subsections (a) through (d) below, a good~~  
17 |           ~~faith, detailed~~ estimate of the total cost of completion  
18 |           of the interconnection of the proposed system and/or  
19 |           a statement of cost responsibility for a dedicated  
20 |           transformer(s) or other required interconnection  
21 |           equipment:  
22 |  
23 |                (a) with respect to an applicant that is not to be net-  
24 |                metered, an estimate shall be provided and shall  
25 |                include the costs associated with any required  
26 |                modifications to the utility system, administration,  
27 |                metering, and on-site verification testing;  
28 |  
29 |                (b) with respect to an applicant that is to be net-  
30 |                metered and that is a Farm Wind, Farm Waste,  
31 |                Non-Residential Wind, Non-Residential Micro-  
32 |                hydroelectric, Non-Residential Fuel Cell or Non-  
33 |                Residential Solar applicant intending to install ~~wind~~  
34 |                electric generating equipment with a rated capacity  
35 |                of more than 25 kW, an estimate shall be provided  
36 |                and shall include the applicant's responsibility for  
37 |                the actual cost of installing any dedicated  
38 |                transformer(s) and other safety equipment up to the  
39 |                maximum set forth in subsection (c) below;  
40 |  
41 |                (c) with respect to an applicant that is to be net-  
42 |                metered, if the utility determines that it is necessary  
43 |

to install a dedicated transformer(s) or other equipment to protect the safety and adequacy of electric service provided to other customers, the applicant shall be informed of its responsibility for the actual costs for installing the dedicated transformer(s) and other safety equipment. The following table reflects the maximum responsibility each designated applicant shall have with respect to the actual cost of the dedicated transformer(s) and other safety equipment:

Appendix D sets forth the responsibility each applicant shall have with respect to the actual cost of the dedicated transformer(s) and other safety equipment.

**Maximum Expense for Dedicated Transformer and Other Safety Equipment for Net Metered Customers (Up to 2 MW)**

Generator Type	Generator Size	Maximum Equipment Cost to Customer
Solar / Micro-hydroelectric	Over 25 kW up to 2 MW	As determined by Utility*
Fuel Cell	Over 10 kW up to 1.5 MW	As determined by Utility*
Wind	Over 25 kW up to 2 MW	As determined by Utility*
Farm Wind	Over 25 kW up to 500 kW	\$5,000
Farm Waste	Up to 1 MW	\$5,000

\* Subject to review by the Commission at the request of the Customer

**STEP 7: Applicant Commits to Utility Construction of Utility’s System Modifications.**

The applicant and utility will execute the New York Standardized Contract ~~a standardized contract~~ for interconnection and the applicant will provide the utility with an advance payment for the utility’s estimated costs as identified in Step 6 (estimated costs will be reconciled with actual costs in Step 11).

**STEP 8: Project Construction.**

The applicant will build the facility in accordance with the utility-accepted design. The utility may require the applicant to provide a copy of the electrical inspection certificate upon completion of construction and in advance of verification testing in Step 9 as supporting documentation that the facility is ready for verification testing.

1 | The utility will commence construction/installation of system modifications and metering  
2 | requirements as identified in Step 6. Utility system modifications will vary in  
3 | construction time depending on the extent of work and equipment required. The schedule  
4 | for this work is to be discussed and agreed upon with the applicant in Step 6.

5 |  
6 | **STEP 9: The Applicant's Facility is Tested in Accordance ~~with~~With the**  
7 | **Standardized Interconnection Requirements.**  
8 | **~~Interconnection Requirements~~.**  
9 |

10 | The verification testing will be performed by the applicant in accordance with the written  
11 | test procedure(s) provided by the applicant in Step 5 and any site-specific requirements  
12 | identified by the utility in Step 6. The final verification testing will be conducted within  
13 | ten (10) Business Days~~business days~~ of complete installation at a mutually agreeable  
14 | time, and the utility shall be given the opportunity to witness the tests. If the utility opts  
15 | not to witness the ~~test~~test, the applicant will send the utility within five (5) Business  
16 | Days~~days~~ of completion of such testing~~the test~~ a written notification, certifying that the  
17 | system has been installed and tested in compliance with the SIR, the utility-accepted  
18 | design, and the equipment manufacturer's instructions.

19 |  
20 | **STEP 10: Interconnection.**  
21 |  
22 |

23 | The applicant's facility will be allowed to commence parallel operation upon satisfactory  
24 | completion of the tests in Step 9 and receipt of the electrical inspection certificate if  
25 | required. ~~—In addition, the applicant must have complied with and must continue to~~  
26 | ~~comply with the contractual and technical requirements.~~  
27 |

28 | **STEP 11: Final Acceptance and Utility Cost Reconciliation.**  
29 |

30 | If the utility witnessed the verification testing, then, within ten (10) Business  
31 | Days~~business days~~ of the completion of such testing, and receipt of the electrical  
32 | inspection certificate, if required~~test~~, the utility will issue to the applicant either a formal  
33 | letter of acceptance for interconnection or a detailed explanation of the deficiencies in the  
34 | system. If the utility did not witness the verification testing, then, within ten (10)  
35 | Business Days~~business days~~ of receiving the written test notification from Step 9, the  
36 | utility will either issue to the applicant a formal letter of acceptance for interconnection,  
37 | or in the event that the utility cannot accept the verification test results as presented, the  
38 | utility will request that the applicant and utility set a date and time for for the applicant to  
39 | re-perform thean on-site verification tests in order to allow the utility toand witness the  
40 | conduct of the verification tests and the operation of the DG system. This witnessed~~joint~~  
41 | on-site verification testing must be completed within twenty (20) Business Days~~business~~  
42 | days after being requested. Within ten (10) Business Days~~business days~~ of the

1 | completion of any such witnessed testing~~the on-site verification~~, the utility will issue to  
2 | the applicant either a formal letter of acceptance for interconnection or a detailed  
3 | explanation of the deficiencies in the system. The receipt of such formal letter of  
4 | acceptance does not relieve the applicant from continuing to comply with all contractual  
5 | and technical requirements and the applicant shall abide by such requirements as long as  
6 | the DG system is interconnected to the utility's system.- At this time, the utility will also  
7 | reconcile its actual costs related to the applicant's project against the application fee and  
8 | advance payments made by the applicant. The applicant will receive either a bill for any  
9 | balance due or a reimbursement for overpayment as determined by the utility's  
10 | reconciliation, except that a net metering applicant may not be charged in excess of the  
11 | cost of installing the dedicated transformer(s) or other safety equipment described above  
12 | in Step 6. The applicant may contest the reconciliation with the utility. If the applicant is  
13 | not satisfied, a formal complaint may be filed with the Commission.  
14 |  
15 |

#### 16 | **D. Web-Based Standard Interconnection Requirements**

17 |  
18 | Each utility shall implement and maintain a web-based system to provide customers and  
19 | contractors current information regarding the status of their SIR application process. The  
20 | system shall be customer specific and post the current status of the SIR process. At a  
21 | minimum the following content shall be provided:

- 22 | 1. The applicant's name and project/application identification number.
- 23 | 2. Description of the project, including at a minimum, the project's type (energy  
24 | source), size, metering, and location.
- 25 | 3. SIR project application status, including all the steps completed and to be  
26 | completed, along with corresponding completion/deadline dates associated with  
27 | each step.
  - 28 | • If the next action is to be taken by the utility, the expected date that action  
29 | will be completed,
  - 30 | • If the next action is to be taken by the applicant, what exactly is required  
31 | and a contact for more information,
- 32 | 4. Information regarding any outstanding information request made by the utility of  
33 | the applicant, and
- 34 | 5. The status of all amounts paid and/or due to the utility by the applicant.

35 |  
36 | Access shall be available for the customer and their authorized  
37 | agent(s), contractor, such that both can access the information. The web site must be,  
38 | however, secure and private from unauthorized access.  
39 |

40 | The utility web site shall also provide the ability for applicants with systems 25  
41 | kW and less to submit their application for interconnection via the web. The web-based  
42 | application process must be consistent with Appendix B of the SIR and include the ability  
43 | to attach associated documentation or drawings associated with each project.

1

2 |

1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42

**Section II. Interconnection Requirements**

**A. Design Requirements**

**1. Common**

The generator-owner shall provide appropriate protection and control equipment, including a protective device that utilizes an automatic disconnect device that will disconnect the generation in the event that the portion of the utility system that serves the generator is de-energized for any reason or for a fault in the generator-owner’s system. The generator-owner’s protection and control equipment shall be capable of automatically disconnecting the generation upon detection of an islanding condition and upon detection of a utility system fault.

The generator-owner’s protection and control scheme shall be designed to ensure that the generation remains in operation when the frequency and voltage of the utility system is within the limits specified by the required operating ranges. Upon request from the utility, the generator-owner shall provide documentation detailing compliance with the requirements set forth in this document.

The specific design of the protection, control and grounding schemes will depend on the size and characteristics of the generator-owner’s generation, as well the generator-owner’s load level, in addition to the characteristics of the particular portion of the utility’s system where the generator-owner is interconnecting.

The generator-owner shall have, as a minimum, an automatic disconnect device(s) sized to meet all applicable local, state, and federal codes and operated by over and under voltage and over and under frequency protection. For three-phase installations, the over and under voltage function should be included for each phase and the over and under frequency protection on at least one phase. All phases of a generator or inverter interface shall disconnect for voltage or frequency trip conditions sensed by the protective devices. Voltage protection shall be wired phase to ground for single phase installations and for applications using wye grounded-wye grounded service transformers.

The settings below are listed for single-phase and three-phase applications using wye grounded-wye grounded service transformers or wye grounded-wye grounded isolation transformers. For applications using other transformer connections, a site-specific review will be conducted by the utility and the revised settings identified in Step 6 of the Application Process.

1  
2 The requirements set forth in this document are intended to be consistent with those  
3 contained in the most current version of IEEE Std 1547, *Standard for Interconnecting*  
4 *Distributed Resources with Electric Power Systems*. The requirements in IEEE Std 1547  
5 above and beyond those contained in this document shall be followed<sup>†</sup>;

### 6 7 Voltage Response

8  
9 The required operating range for the generators shall be from 88% to 110% of nominal  
10 voltage magnitude. For excursions outside these limits the protective device shall  
11 automatically initiate a disconnect sequence from the utility system as detailed in the  
12 most current version of IEEE Std 1547. Clearing time is defined as the time the range is  
13 initially exceeded until the generator-owner's equipment ceases to energize the PCC and  
14 includes detection and intentional time delay.

### 15 16 Frequency Response

17  
18 The required operating range for the generators shall be from 59.3 Hz to 60.5 Hz. For  
19 generators greater than 30 kW the utility may request that the generator operate at  
20 frequency ranges below 59.3 Hz as defined in IEEE Std 1547. For excursions outside  
21 these limits the protective device shall automatically initiate a disconnect sequence from  
22 the utility system as detailed in the most current version of IEEE Std 1547. Clearing time  
23 is defined as the time the range is initially exceeded until the generator-owner's  
24 equipment ceases to energize the PCC and includes detection and intentional time delay.

25  
26 If the generation facility is disconnected as a result of the operation of a protective  
27 device, the generator-owner's equipment shall remain disconnected until the utility's  
28 service voltage and frequency have recovered to acceptable voltage and frequency limits  
29 for a minimum of five (5) minutes. Systems greater than 25 kW that do not utilize  
30 inverter based interface equipment shall not have automatic recloser capability unless  
31 otherwise approved by the utility. If the utility determines that a facility must receive  
32 permission to reconnect, then any automatic reclosing functions must be disabled and  
33 verified to be disabled during verification testing.

## 34 35 **2. Synchronous Generators**

36  
37 Synchronous generation shall require synchronizing facilities. These shall include  
38 automatic synchronizing equipment or manual synchronizing with relay supervision,  
39 voltage regulator, and power factor control.

40  

---

<sup>†</sup> ~~It is expected that IEEE Std 1547 will eventually supersede the need for explicit technical standards in New York State. However, until such time as all IEEE 1547 series of standards are complete and approved, this standard will take precedence.~~

1 For all synchronous generators sufficient reactive power capability shall be provided by  
2 the generator-owner to withstand normal voltage changes on the utility's system. The  
3 generator voltage VAR schedule, voltage regulator, and transformer ratio settings shall be  
4 jointly determined by the utility and the generator-owner to ensure proper coordination of  
5 voltages and regulator action. Generator-owners shall have synchronous generator  
6 reactive power capability to withstand voltage changes up to 5% of the base voltage  
7 levels.

8 |  
9 A voltage regulator must be provided and be capable of maintaining the generator voltage  
10 under steady state conditions within plus or minus 1.5% of any set point and within an  
11 operating range of plus or minus 5% of the rated voltage of the generator.

12  
13 Generator-owners shall adopt one of the following grounding methods for synchronous  
14 generators:

- 15  
16 | a) Solid grounding  
17 |  
18 | b) High- or low-resistance grounding  
19 |  
20 | c) High- or low-reactance grounding  
21 |  
22 | d) Ground fault neutralizer grounding  
23

24 Synchronous generators shall not be permitted to connect to utility secondary network  
25 systems without the ~~acceptance~~approval of the utility.

### 26 27 | **3. Induction Generators** 28 | 29 |

30 Induction generation may be connected and brought up to synchronous speed (as an  
31 induction motor) if it can be demonstrated that the initial voltage drop measured at the  
32 PCC is acceptable based on current inrush limits. The same requirements also apply to  
33 induction generation connected at or near synchronous speed because a voltage dip is  
34 present due to an inrush of magnetizing current. The generator-owner shall submit the  
35 expected number of starts per specific time period and maximum starting kVA draw data  
36 to the utility. ~~to verify that the voltage dip due to starting is within the visible flicker~~  
37 ~~limits as defined by IEEE Std 519, Recommended Practices and Requirements for~~  
38 ~~Harmonic Control in Electric Power Systems.~~

39  
40 Starting or rapid load fluctuations on induction generators can adversely impact the  
41 utility's system voltage. Corrective step-switched capacitors or other techniques may be  
42 necessary. These measures can, in turn, cause ferroresonance. If these measures

1 (additional capacitors) are installed on the customer's side of the PCC, the utility will  
2 review these measures and may require the customer to install additional equipment.

#### 3 4 **4. Inverters**

5  
6 Direct current generation can only be installed in parallel with the utility's system using a  
7 synchronous inverter. The design shall be such as to disconnect this synchronous inverter  
8 upon a utility system interruption.

9  
10 It is recommended that equipment be selected from the Department of Public Service  
11 "Certified Interconnection Equipment" list maintained only by the Commission's  
12 website.PSC. Interconnected ~~DG~~Distributed Generating systems utilizing equipment not  
13 found listed in such the "Certified Equipment" list must meet all functional requirements  
14 of the current version of IEEE Std 1547 and be protected by utility grade relays (as  
15 defined in these requirements) using settings approved by the utility and verified in the  
16 field. The field verification test must demonstrate that the equipment meets the voltage  
17 and frequency requirements detailed in this section.

18  
19 Synchronization or re-synchronization of an inverter to the utility system shall not result  
20 in a voltage deviation that exceeds the requirements contained in Section II.E, Power  
21 Quality. Only inverters designed to operate in parallel with the utility system shall be  
22 utilized for that purpose.

23  
24 ~~A line inverter can be used to isolate the customer from the utility system provided it can~~  
25 ~~be demonstrated that the inverter isolates the customer from the utility system safely and~~  
26 ~~reliably.~~

#### 27 28 **5. Minimum Protective Function Requirements**

29  
30 Protective system requirements for distributed generation facilities result from an  
31 assessment of many factors, including but not limited to:

- 32 |
- 33 • Type and size of the distributed generation facility
  - 34 • Voltage level of the interconnection
  - 35 • Location of the distributed generation facility on the circuit
  - 36 • Distribution transformer
  - 37 • Distribution system configuration
  - 38 • Available fault current
  - 39 • Load that can remain connected to the distributed generation facility under isolated
  - 40 conditions
  - 41 • Amount of existing distributed generation on the local distribution system.
- 42

1 As a result, protection requirements ~~cannot~~ be standardized according to any  
2 single criteria.

3 Minimum protective function requirements shall be as detailed in the table below. ANSI  
4 C37.2, Electric Power System Device Function Numbers, are listed with each function.  
5  
6  
7  
8  
9

Synchronous Generators	Induction Generators	Inverters
Over/Under Voltage (Function 27/59)	Over/Under Voltage (Function 27/59)	Over/Under Voltage (Function 27/59)
Over/Under Frequency (Function 81O/81U)	Over/Under Frequency (Function 81O/81U)	Over/Under Frequency (Function 81O/81U)
<u>Anti-Islanding Protection</u>	<u>Anti-Islanding Protection</u>	Anti-Islanding Protection

10  
11  
12 The need for additional protective functions shall be determined by the utility on a case-  
13 by-case basis. If the utility determines a need for additional functions, it shall notify the  
14 generator-owner in writing of the requirements. The notice shall include a description of  
15 the specific aspects of the utility system that necessitate the addition, and an explicit  
16 justification for the necessity of the enhanced capability. The utility shall specify and  
17 provide settings for those functions that the utility designates as being required to satisfy  
18 protection practices. Any protective equipment or setting specified by the utility shall not  
19 be changed or modified at any time by the generator-owner without written consent from  
20 the utility.  
21

22 The generator-owner shall be responsible for ongoing compliance with all applicable  
23 local, state, and federal codes and standardized interconnection requirements as they  
24 pertain to the interconnection of the generating equipment. Protective devices shall  
25 utilize their own current transformers and potential transformers and not share electrical  
26 equipment associated with utility revenue metering.  
27

28 A failure of the generator-owner's protective devices, including loss of control power,  
29 shall open the automatic disconnect device, thus disconnecting the generation from the  
30 utility system. A generator-owner's protection equipment shall utilize a non-volatile  
31 memory design such that a loss of internal or external control power, including batteries,  
32 will not cause a loss of interconnection protection functions or loss of protection set  
33 points.  
34

35 All interface protection and control equipment shall operate as specified independent of  
36 the calendar date.

1  
2 **6. Metering**  
3

4 The need for additional revenue metering or modifications to existing metering will be  
5 reviewed on a case-by-case basis and shall be consistent with metering requirements  
6 adopted by the Commission.  
7

8 Any incremental metering costs are included in interconnection costs that may be  
9 required of an applicant.  
10

11  
12  
13  
14  
15  
16  
17  
18 The following ~~tables summarize~~Table summarizes the New York Net Metering Rules  
19

<b>New York (PSL §66-j) - Net Metering*</b>						
<b>Incentive Type:</b>	Net Metering Rules					
<b>Eligible Renewable/Other Technologies:</b>	Solar / Micro-hydroelectric		Biogas	Micro CHP	Fuel Cell	
<b>Applicable Sectors:</b>	Residential	Non-Residential	Farm-Waste	Residential	Residential	Non-Residential
<b>Limit on System Size:</b>	25 kW	Up to 2 MW	1 MW	10 kW	10 kW	Up to 1.5 MW
<b>Remote Net Metering**</b>	No	<u>Yes***</u>	Yes	No	No	
<b>Limit on Overall Enrollment:</b>	1% of 2005 <u>Electric</u> Demand per IOU for Solar, Biogas, Micro CHP, <u>Micro-hydroelectric</u> and Fuel Cells combined					

1

<b>New York (PSL §66-1) - Net Metering*</b>			
<b>Incentive Type:</b>	Net Metering Rules		
<b>Eligible Renewable/Other Technologies:</b>	Wind		
<b>Applicable Sectors:</b>	Residential	Non-Residential	Farm-Service Wind
<b>Limit on System Size:</b>	25 kW	Up to 2 MW	500 kW
<b>Remote Net Metering**</b>	No	Yes	Yes
<b>Limit on Overall Enrollment:</b>	.3% of 2005 Demand per IOU		

2

3

4

5

6

7

8

9

10

11

12

13

14

15

16

17

\* Refer to specific utility tariff leaves for more detailed rules and regulations applicable to net metering.

18

19

~~\*\* Per the Public Service Law (PSL) §66-j & 66-l, Remote Net Metering allows non-residential solar photovoltaic, farm waste, farm wind, and non-residential wind customers, to apply excess generation credits from the customer's generator to certain other meters on property that is owned or leased by the same customer.~~

21

22

23

~~\*\*\*Non-residential solar customers are eligible for remote net metering; non-residential micro-hydroelectric customers are not eligible for remote net metering~~

24

25

26

27

### **B. Operating Requirements**

28

29

The generator-owner shall provide a 24-hour telephone contact. This contact will be used by the utility to arrange access for repairs, inspection or emergencies. The utility will

30

1 make such arrangements (except for emergencies) during normal business hours.

2 |  
3 Voltage and frequency trip set point adjustments shall be accessible to service personnel  
4 only.

5 Any changes to these settings must be reviewed and approved by the utility.

6  
7 The generator-owner shall not supply power to the utility during any outages of the utility  
8 system that serves the PCC. The generator-owner's generation may be operated during  
9 such outages only with an open tie to the utility. Islanding will not be permitted. The  
10 generator-owner shall not energize a de-energized utility circuit for any reason.

11 |  
12 The disconnect switch specified for system size larger than ~~25 kW~~ 25kW and non-inverter  
13 based systems of 25 kW or less in Section II.D, Disconnect Switch, may be opened by  
14 the utility at any time for any of the following reasons:

- 15  
16 a. to eliminate conditions that constitute a potential hazard to  
17 utility personnel or the general public;  
18  
19 b. pre-emergency or emergency conditions on the utility system;  
20  
21 c. a hazardous condition is revealed by a utility inspection;  
22  
23 d. protective device tampering;  
24  
25 e. parallel operation prior to utility approval to interconnect.  
26

27 The disconnect switch may be opened by the utility for the following reasons, after notice  
28 to the responsible party has been delivered and a reasonable time to correct (consistent  
29 with the conditions) has elapsed:

- 30  
31 a. A generator-owner has failed to make available records of  
32 verification tests and maintenance of its protective devices;  
33  
34 b. A generator-owner's system adversely impacts the operation of  
35 utility equipment or equipment belonging to other utility  
36 customers;  
37  
38 c. A generator-owner's system is found to adversely affect the  
39 quality of service to adjoining customers.  
40

41 The utility will provide a name and telephone number so that the generator-owner can  
42 obtain information about the utility lock-out.  
43

1 The generator-owner shall be allowed to disconnect from the utility without prior notice  
2 in order to self generate.

3  
4 Under certain conditions a utility may require direct transfer trip (DTT). The utility shall  
5 provide detailed evidence as to the need for DTT.

6  
7 If a generator-owner proposes any modification to the system that has an impact on the  
8 interface at the PCC after it has been installed and a contract between the utility and the  
9 generator-owner has already been executed, then any such modifications must be  
10 reviewed and approved by the utility before the modifications are made.

### 11 12 **C. Dedicated Transformer**

13  
14 The utility reserves the right to require a power-producing facility to connect to the utility  
15 system through a dedicated transformer. The transformer shall either be provided by the  
16 connecting utility at the generator-owner's expense, purchased from the utility, or  
17 conform to the connecting utility's specifications. The transformer may be necessary to  
18 ensure conformance with utility safe work practices, to enhance service restoration  
19 operations or to prevent detrimental effects to other utility customers. The transformer  
20 that is part of the normal electrical service connection of a generator-owner's facility may  
21 meet this requirement if there are no other customers supplied from it. A dedicated  
22 transformer is not required if the installation is designed and coordinated with the utility  
23 to protect the utility system and its customers adequately from potential detrimental net  
24 effects caused by the operation of the generator.

25  
26 If the utility determines a need for a dedicated transformer, it shall notify the generator-  
27 owner in writing of the requirements. The notice shall include a description of the  
28 specific aspects of the utility system that necessitate the addition, the conditions under  
29 which the dedicated transformer is expected to enhance safety or prevent detrimental  
30 effects, and the expected response of a normal, shared transformer installation to such  
31 conditions.

### 32 33 **D. Disconnect Switch**

34  
35 Generating equipment with system size larger than 25 kW and non-inverter based  
36 systems of 25 kW or less shall be capable of being isolated from the utility system by  
37 means of an external, manual, visible, gang-operated, load break disconnecting switch.  
38 The disconnect switch shall be installed, owned, and maintained by the customer-  
39 generator, and located between the generating equipment and its interconnection point  
40 with the utility system.

41  
42 The disconnect switch must be rated for the voltage and current requirements of the  
43 installation.

1  
2 The basic insulation level (BIL) of the disconnect switch shall be such that it will  
3 coordinate with that of the utility's equipment. Disconnect devices shall meet applicable  
4 requirements of the most current version of UL, ANSI, and IEEE standards, and shall be  
5 installed to meet all applicable local, state, and federal codes. (New York City Building  
6 Code may require additional certification.)

7  
8 The disconnect switch shall be clearly marked, "Generator Disconnect Switch," with  
9 permanent 3/8 inch or larger letters or larger.

10  
11 The disconnect switch shall be located within 10 feet of the utility's external electric  
12 service meter. If such location is not possible, the customer-generator will propose, and  
13 the utility will approve, an alternate location. The location and nature of the disconnect  
14 switch shall be indicated in the immediate proximity of the electric service entrance. The  
15 disconnect switch shall be readily accessible for operation and locking by utility  
16 personnel in accordance with Section II.B, Operating Requirements. The disconnect  
17 switch must be lockable in the open position with a 3/8" shank utility padlock.

18  
19 For installations above 600V or with a full load output of greater than 960A, a draw-out  
20 type circuit breaker with the provision for padlocking at the draw-out position will not be  
21 an acceptable disconnect switch for the purposes of this requirement unless the use of  
22 such a circuit breaker is specifically granted by the utility, based on site-specific technical  
23 requirements. If the utility grants such use, the generator-owner will be required, upon  
24 the utility's request, to provide qualified operating personnel to open the draw-out circuit  
25 breaker and ensure isolation of the DG system, with such operation to be witnessed by  
26 the utility followed immediately by the utility locking the device to prevent re-  
27 energization. In an emergency or outage situation, where there is no access to the draw-  
28 out breaker or no qualified personnel, utilities may disconnect the electric service to the  
29 premise in order to isolate the DG system ~~can be considered a disconnect switch for the~~  
30 ~~purposes of this requirement.~~

31  
32 **E. Power Quality**

33  
34 The maximum harmonic limits for electrical equipment shall be in accordance with IEEE  
35 519 to limit the maximum individual frequency voltage harmonic to 3% of the  
36 fundamental frequency and the voltage Total Harmonic Distortion (THD) to 5% on the  
37 utility side of the PCC. In addition, any voltage fluctuation resulting from the connection  
38 of the customer's energy producing equipment to the utility system must not exceed the  
39 limits defined by the maximum permissible voltage fluctuations border line of visibility  
40 curve, ~~identified in IEEE Std 519.~~ This requirement is necessary to minimize the adverse  
41 voltage effect upon other customers on the utility system.

42  
43 **F. Power Factor**

1  
2 If the average power factor, as measured at the PCC, is less than 0.9 (leading or lagging),  
3 the method of power factor correction necessitated by the installation of the generator  
4 will be negotiated with the utility as a commercial item.  
5

6 Induction power generators may be provided VAR capacity from the utility system at the  
7 generator-owner's expense. The installation of VAR correction equipment by the  
8 generator-owner on the generator-owner's side of the PCC must be reviewed and  
9 approved by the utility prior to installation.  
10

### 11 **G. Islanding**

12  
13 Generation interconnection systems must be designed and operated so that islanding is  
14 not sustained on utility distribution circuits. The requirements listed in this document are  
15 designed and intended to prevent islanding.  
16

### 17 **H. Equipment Certification**

18  
19 In order for the equipment to be acceptable for interconnection to the utility system  
20 without additional protective devices, the interface equipment must be equipped with the  
21 minimum protective function requirements listed in the table in Section II.A.5 and be  
22 tested by a Nationally Recognized Testing Laboratory (NRTL) recognized by the United  
23 States Occupational Safety and Health Administration (OSHA) in compliance with the  
24 most current version of UL 1741. Underwriter's Laboratories (UL) 1741, Inverters,  
25 Converters, Controllers and Interconnection System Equipment for Use With Distributed  
26 Energy Resources (January 28, 2010 revision).  
27

28 For each interconnection application, documentation including the proposed equipment  
29 certification, stating compliance with UL 1741 by an NRTL, shall be provided by the  
30 applicant to the utility. Supporting information from an NRTL website or UL's website  
31 stating compliance is acceptable for documentation.  
32

33 If an equipment manufacturer, vendor, or any other party desires, documentation  
34 indicating compliance as stated above may be submitted to DPS Staff for inclusion in the  
35 listing under the the Department of Public Service Commission for listing under the  
36 "Certified Interconnection Equipment ("Certified Equipment")" list on the  
37 Commission's Department's website (<http://www.dps.ny.gov/distgen.htm>).  
38

39 Certification information for equipment tested and certified to the most current version of  
40 UL 1741 (January 28, 2010 revision) by a non-NRTL shall be provided by the  
41 manufacturer, or vendor to the contacts listed on the Public Service Commission's  
42 website (<http://www.dps.ny.gov/distgen.htm>)—for review before final  
43 acceptance approval and posting under the Public Service Commission's "Certified

1 | Equipment<sup>22</sup> list. Utilities are not responsible for reviewing and approving equipment  
2 | tested and certified by a non-NRTL.

3 |  
4 | If ~~an~~ equipment is UL 1741 ~~(January 28, 2010 revision)~~ certified by an NRTL and  
5 | compliance documentation is submitted to the utility, the utility shall accept such  
6 | equipment for interconnection in New York state. All equipment certified to the most  
7 | current version of UL 1741 ~~(January 28, 2010 revision)~~ by an NRTL shall be deemed  
8 | ‘certified equipment’ even if it does not appear on the ~~Department of Public Service~~  
9 | Commission’s website under the Certified Equipment list.

10 |  
11 | Utility grade relays need not be certified per the requirements of this section.

## 12 | 13 | 14 | 15 | **I. Verification Testing**

16 |  
17 | All interface equipment must include a verification test procedure— as part of the  
18 | documentation presented to the utility. Except for the case of small single-phase  
19 | inverters as discussed later, the verification test must establish that the protection settings  
20 | meet the SIR requirements. The verification testing may be site-specific and is conducted  
21 | periodically to assure continued acceptable performance.

22 |  
23 | Upon initial parallel operation of a generating system, or any time interface hardware or  
24 | software is changed, the verification test must be performed. A qualified individual must  
25 | perform verification testing in accordance with the manufacturer’s published test  
26 | procedure. Qualified individuals include professional engineers, factory-trained and  
27 | certified technicians, and licensed electricians with experience in testing protective  
28 | equipment. The utility reserves the right to witness verification testing or require written  
29 | certification that the testing was successfully performed.

30 |  
31 | Verification testing shall be performed at least once every four years. All verification  
32 | tests prescribed by the manufacturer shall be performed. If wires must be removed to  
33 | perform certain tests, each wire and each terminal must be clearly and permanently  
34 | marked. The generator-owner shall maintain verification test reports for inspection by  
35 | the utility.

36 |  
37 | Single-phase inverters and inverter systems rated 25 kW and below shall be verified upon  
38 | initial parallel operation and once every four years as follows: the generator-owner shall  
39 | interrupt the utility source and verify that the equipment automatically disconnects and  
40 | does not reconnect for at least five minutes after the utility source is reconnected. The  
41 | owner shall maintain a log of these operations for inspection by the connecting utility.  
42 | Any system that depends upon a battery for trip power shall be checked and logged at  
43 | least annually for proper voltage. Once every four (4) years the battery must be either

1 replaced or a discharge test performed.

2

3 **J. Interconnection Inventory**

4

5 To ensure applications are addressed in a timely manner and monitor the overall  
6 interconnection activities, utilities shall submit an SIR inventory of projects to the Public  
7 Service Commission by January 31 and July 31 of each year. At a minimum the  
8 following information shall be provided in the inventory:

9

10

1. Utility Name

11

~~1. Company~~

12

2. Applicant Name

13

3. System Type

14

4. System Capacity

15

5. Net Metered (Yes/No)

16

6. Protective Equipment

17

7. Application Review Start and End date

18

8. Preliminary Review Start and End date

19

9. CESIR Start and End date

20

10. CESIR Costs

21

11. Verification Testing date

22

12. Final Letter of Acceptance date

23

13. Total percentage of SIR connected demand

24

25

26

27

### Section III. Glossary of Terms

**Automatic Disconnect Device:** An electronic or mechanical switch used to isolate a circuit or piece of equipment from a source of power without the need for human intervention.

**Business Day:** Monday through Friday, excluding utility holidays.

**Cease to Energize:** Cessation of energy flow capability

**Coordinated Electric System Interconnection Review:** Any studies performed by utilities to ensure that the safety and reliability of the electric grid with respect to the interconnection of distributed generation as discussed in this document.

**Customer-Generator:** A utility customer who owns or operates electric generating equipment located and used at the customer's premises, and/or the utility customer's agent.

**Dedicated Transformer:** A transformer installed by the utility to isolate with a DG system secondary winding that may have a negative impact on the power quality of other customers serves only one customer.

**Direct Transfer Trip:** Remote operation of a circuit breaker by means of a communication channel.

**Disconnect (verb):** To isolate a circuit or equipment from a source of power. If isolation is accomplished with a solid-state device, "Disconnect" shall mean to cease the transfer of power.

**Disconnect Switch:** A mechanical device used for isolating a circuit or equipment from a source of power.

**Draw-out Type Circuit Breaker:** Circuit breakers that are disconnected by physically separating, or racking, the breaker assembly away from the switchgear bus.

**Farm Waste, Net Meter, Farm Applicant:** A farm applicant who is proposing to install a farm waste anaerobic digester generating system, not to exceed 1 MW, at a farm, per the requirements of New York State Public Service Law §66-j.

**Fuel Cell, Net Meter, Residential Applicant:** A residential applicant who is proposing to install a fuel cell electric generating system located and used at the applicant's

1 | premises, not to exceed a combined rated capacity of not more than 10 kW, per the  
2 | requirements of New York State Public Service Law §66-j.

3 |  
4 | **Fuel Cell, Net Meter, Non-Residential Applicant:** A non-residential applicant who is  
5 | proposing to install a fuel cell electric generating system located and used at the  
6 | applicant's premises, not to exceed a combined rated capacity of not more than 1.5 MW,  
7 | per the requirements of New York State Public Service Law §66-j.

8 |  
9 | **Generator-Owner:** An applicant to operate on-site power generation equipment in  
10 | parallel with the utility grid per the requirements of this document.

11 |  
12 | **Islanding:** A condition in which a portion of the utility system that contains both load  
13 | and distributed generation is isolated from the remainder of the utility system. (Adopted  
14 | from  
15 | IEEE Std 929.)

16 |  
17 | **Micro-Combined Heat and Power, Net Meter, Residential Applicant:** A residential  
18 | applicant who is proposing to install a micro-combined heat and power (Micro-~~C~~HP)  
19 | generating system located and used at the applicant's premises, not to exceed 10 kW, per  
20 | the requirements of New York State Public Service Law §66-j.

21 |  
22 | **Micro-Hydroelectric, Net Meter, Residential Applicant:** A residential applicant who  
23 | is proposing to install a micro-hydroelectric generating equipment located and used at the  
24 | applicant's premises, not to exceed 25 kW, per the requirement of New York State Public  
25 | Service Law §66-j.

26 |  
27 | **Micro-Hydroelectric, Net Meter, Non-Residential Applicant:** A non-residential  
28 | applicant who is proposing to install a micro-hydroelectric generating equipment located  
29 | and used at the applicant's premises, not to exceed 2 MW, per the requirement of New  
30 | York State Public Service Law §66-j.

31 |  
32 | **Point of Common Coupling:** The point at which the interconnection between the  
33 | electric utility and the customer interface occurs. Typically, this is the customer side of  
34 | the utility revenue meter.

35 |  
36 | **Preliminary Review:** A review of the generator-owner's proposed system capacity,  
37 | location on the utility system, system characteristics, and general system regulation to  
38 | determine if the interconnection is viable.

39 |  
40 | **Protective Device:** A device that continuously monitors a designated parameter related  
41 | to the operation of the generation system that operates if preset limits are exceeded  
42 |

1 **Remote Net Metering:** Per the Public Service Law (PSL) §66-j & §66-l Remote Net  
2 Metering allows customers with non-residential solar photovoltaic, farm waste, farm  
3 wind, non-residential micro-hydroelectric ~~or~~ non-residential wind  
4 generation customers, to apply excess generation credits from the customer's generator to  
5 certain other meters on property that is owned or leased by the same customer and  
6 located within the service territory of the same utility to which the customer-generator's  
7 net energy meters are interconnected and within the same load zone. A satellite account  
8 cannot itself be net metered.

9  
10 **Required Operating Range:** The range of magnitudes of the utility system voltage or  
11 frequency where the generator-owner's equipment, if operating, is required to remain in  
12 operation for the purposes of compliance with UL 1741. Excursions outside these ranges  
13 must result in the automatic disconnection of the generation within the prescribed time  
14 limits

15  
16 **Safety Equipment:** Includes dedicated transformers or equipment and facilities to  
17 protect the safety and adequacy of electric service provided to other customers.

18  
19 **Solar, Net Meter, Residential Applicant:** A residential applicant who is proposing to  
20 install a photovoltaic generating system, not to exceed 25 kW, in an owner occupied  
21 residence per the requirements of New York State Public Service Law §66-j.

22  
23 **Solar, Net Meter, Non-Residential Applicant:** A non-residential applicant who is  
24 proposing to install a solar generating system located and used at the applicant's  
25 premises, not to exceed 2 MW, pursuant to New York State Public Service Law §66-j.

26  
27 **Utility Grade Relay:** A relay that is constructed to comply with, as a minimum, the  
28 most current version of the following standards for non-nuclear facilities:

<u>Standard</u>	<u>Conditions Covered</u>
<u>ANSI/IEEE C37.90</u>	Usual Service Condition Ratings - Current and Voltage Maximum design for all relay AC and DC auxiliary relays Make and carry ratings for tripping contacts Tripping contacts duty cycle Dielectric tests by manufacturer Dielectric tests by user
<u>ANSI/IEEE C37.90.1</u>	Surge Withstand Capability (SWC) Fast Transient Test

1	<u>IEEE C37.90.2</u>	Radio Frequency Interference
2	<u>IEEE C37.98</u>	<del>—</del> Seismic Testing (fragility) of Protective and Auxiliary
3	Relays	
4	<u>ANSI C37.2</u>	Electric Power System Device Function Numbers
5	<u>IEC 255-21-1</u>	Vibration
6	<u>IEC 255-22-2</u>	Electrostatic Discharge
7	<u>IEC 255-5</u>	Insulation (Impulse Voltage Withstand)

8  
9 **Verification Test:** A test performed upon initial installation and repeated periodically to  
10 determine that there is continued acceptable performance.

11  
12 **Wind, Net Meter, Residential Applicant:** A residential applicant who is proposing to  
13 install a wind electric generating system, not to exceed a combined rated capacity of 25  
14 kW, located and used at the applicant's primary residence, per the requirements of New  
15 York State Public Service Law §66-1.

16  
17 **Wind, Net Meter, Non-Residential Applicant:** A non-residential applicant who is  
18 proposing to install a wind electric generating system located and used at the applicant's  
19 premises, not to exceed 2 MW, pursuant to New York State Public Service Law §66-1.

20  
21 **Wind, Net Meter, Farm Applicant:** A farm applicant who is proposing to install a wind  
22 electric generating system, not to exceed a combined rated capacity of 500 kW, located  
23 and used at the applicant's primary residence, per the requirements of New York State  
24 Public Service Law §66-1.

25  
26

1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43

APPENDIX A

NEW YORK STATE  
STANDARDIZED CONTRACT  
FOR INTERCONNECTION OF NEW DISTRIBUTED GENERATION UNITS  
WITH CAPACITY OF 2 MW OR LESS CONNECTED IN PARALLEL WITH  
UTILITY DISTRIBUTION SYSTEMS

**Customer Information:**

**Utility Company Information:**

Name: \_\_\_\_\_

Name: \_\_\_\_\_

Address: \_\_\_\_\_

Address: \_\_\_\_\_

Telephone: \_\_\_\_\_

Telephone: \_\_\_\_\_

Fax: \_\_\_\_\_

Fax: \_\_\_\_\_

Email: \_\_\_\_\_

Email: \_\_\_\_\_

Unit Application/File No. \_\_\_\_\_

Utility Account Number: \_\_\_\_\_

**DEFINITIONS**

**Dedicated Facilities** means the equipment and facilities on the Utility's Company's system necessary to permit operation of the Unit in parallel with the Utility's Company's system.

**Delivery Service** means the services the Utility Company may provide to deliver capacity or energy generated by Customer to a buyer to a delivery point(s), including related ancillary services.

**"Net energy metering"** means the use of a net energy meter to measure, during the billing period applicable to a customer-generator, the net amount of electricity supplied by an electric corporation and provided to the corporation by a customer-generator.

**"SIR"** means the New York State Standardized Interconnection Requirements for new distributed generation units with a nameplate capacity of 2 MW or less connected in parallel with the Utility's Company's distribution system

**"Unit"** means the distributed generation Unit with a nameplate capacity of 2 MW or less located on the Customer's premises at the time the Utility company approves such Unit for

1 | operation in parallel with the Utility'sCompany's system. This Agreement relates only to  
2 | such Unit, but a new agreement shall not be required if the Customerustomer makes  
3 | physical alterations to the Unit that do not result in an increase in its nameplate generating  
4 | capacity. The nameplate generating capacity of the Unit shall not exceed 2 MW, except for  
5 | fuel cell electric generating units which shall not exceed 1.5 MW.;  
6 |

## 7 | I. TERM AND TERMINATION

8 |  
9 | **1.1 Term:** This Agreement shall become effective when executed by both Parties and  
10 | shall continue in effect until terminated.

11 |  
12 | **1.2 Termination:** This Agreement may be terminated as follows:

- 13 |  
14 | a. The Customer may terminate this Agreement at any time, by giving the  
15 | UtilityCompany sixty (60) days' written notice.  
16 |  
17 | b. Failure by the Customer to seek final acceptance by the UtilityCompany  
18 | within twelve (12) months after completion of the utility construction process  
19 | described in the SIR shall automatically terminate this Agreement.  
20 |  
21 | c. Either Party may, by giving the other Party at least sixty (60) days' prior  
22 | written notice, terminate this Agreement in the event that the other Party is in  
23 | default of any of the material terms and conditions of this Agreement. The  
24 | terminating Party shall specify in the notice the basis for the termination and  
25 | shall provide a reasonable opportunity to cure the default.  
26 |  
27 | d. The UtilityCompany may, by giving the customer at least sixty (60) days' prior  
28 | written notice, terminate this Agreement for cause. The Customer's non-  
29 | compliance with an upgrade to the SIR, unless the Customer's installation is  
30 | "grandfathered," shall constitute good cause.  
31 |

32 | **1.3 Disconnection and Survival of Obligations:** Upon termination of this Agreement  
33 | the Unit will be disconnected from the Utility'sCompany's electric system. The termination  
34 | of this Agreement shall not relieve either Party of its liabilities and obligations, owed or  
35 | continuing at the time of the termination.  
36 |

37 | **1.4 Suspension:** This Agreement will be suspended during any period in which the  
38 | Customer is not eligible for delivery service from the UtilityCompany.  
39 |

## 40 | II. SCOPE OF AGREEMENT

1 **2.1 Scope of Agreement:** This Agreement relates solely to the conditions under which  
2 the UtilityCompany and the Customer agree that the Unit may be interconnected to and  
3 operated in parallel with the Utility'sCompany's system.  
4

5 **2.2 Electricity Not Covered:** The UtilityCompany shall have no duty under this  
6 Agreement to account for, pay for, deliver, or return in kind any electricity produced by the  
7 Facility and delivered into the Utility'sCompany's System unless the system is net metered  
8 as described in Public Service Law Sections 66-j or 66-l.  
9

### 10 11 **III. INSTALLATION, OPERATION AND MAINTENANCE OF UNIT** 12

13 **3.1 Compliance with SIR:** Subject to the provisions of this Agreement, the  
14 UtilityCompany shall be required to interconnect the Unit to the Utility'sCompany's system,  
15 for purposes of parallel operation, if the UtilityCompany accepts the Unit as in compliance  
16 with the SIR. The Customer shall have a continuing obligation to maintain and operate the  
17 Unit in compliance with the SIR.  
18

19 **3.2 Observation of the Unit - Construction Phase:** The UtilityCompany may, in its  
20 discretion and upon reasonable notice, conduct reasonable on-site verifications during the  
21 construction of the Unit. Whenever the UtilityCompany chooses to exercise its right to  
22 conduct observations herein it shall specify to the Customer its reasons for its decision to  
23 conduct the observation. For purposes of this paragraph and paragraphs 3.3 through 3.5, the  
24 term "on-site verification" shall not include testing of the Unit, and verification tests shall  
25 not be required except as provided in paragraphs 3.3 and 3.4.  
26

27 **3.3 Observation of the Unit - Ten-day Period:** The UtilityCompany may conduct on-  
28 site verifications of the Unit and observe the execution of verification testing within a  
29 reasonable period of time, not exceeding ten (10) business days after system installation.  
30 The applicant's facility will be allowed to commence parallel operation upon satisfactory  
31 completion of the verification test. The applicant must have complied with and must  
32 continue to comply with all contractual and technical requirements.  
33

34 **3.4 Observation of the Unit - Post-Ten-day Period:** If the UtilityCompany does not  
35 perform an on-site verification of the Unit and observe the execution of verification testing  
36 within the ten-day period, the Customer will send the Utilityutility within five (5) days of  
37 the verification testing a written notification certifying that the Unit has been installed and  
38 tested in compliance with the SIR, the utility-accepted design and the equipment  
39 manufacturer's instructions. The Customer may begin to produce energy upon  
40 satisfactory completion of the verification test. After receiving the verification test  
41 notification, the UtilityCompany will either issue to the Customerapplicant a formal letter  
42 of acceptance for interconnection, or may request that the applicant and utility set a date  
43 and time to conduct an on-site verification of the Unit and make reasonable inquiries of the

1 Customer, but only for purposes of determining whether the verification tests were properly  
2 performed. The Customer shall not be required to perform the verification tests a second  
3 time, unless irregularities appear in the verification test report or there are other objective  
4 indications that the tests were not properly performed in the first instance.

5  
6 | **3.5 Observation of the Unit - Operations:** The UtilityCompany may conduct on-site  
7 verification of the operations of the Unit after it commences operations if the  
8 | UtilityCompany has a reasonable basis for doing so based on its responsibility to provide  
9 continuous and reliable utility service or as authorized by the provisions of the  
10 | Utility'sCompany's Retail Electric Tariff relating to the verification of customer  
11 installations generally.

12  
13 **3.6 Costs of Dedicated Facilities:** During the term of this Agreement, the  
14 | UtilityCompany shall design, construct and install the Dedicated Facilities. The Customer  
15 shall be responsible for paying the incremental capital cost of such Dedicated Facilities  
16 attributable to the Customer's Unit. All costs associated with the operation and maintenance  
17 of the Dedicated Facilities after the Unit first produces energy shall be the responsibility of  
18 | the UtilityCompany.

#### 19 20 **IV. DISCONNECTION OF THE UNIT**

21  
22 | **4.1 Emergency Disconnection:** The UtilityCompany may disconnect the Unit, without  
23 prior notice to the Customer (a) to eliminate conditions that constitute a potential hazard to  
24 | UtilityCompany personnel or the general public; (b) if pre-emergency or emergency  
25 conditions exist on the UtilityCompany system; (c) if a hazardous condition relating to the  
26 Unit is observed by a Utilityutility inspection; or (d) if the Customer has tampered with any  
27 protective device. The UtilityCompany shall notify the Customer of the emergency if  
28 circumstances permit.

29  
30 | **4.2 Non-Emergency Disconnection:** The UtilityCompany may disconnect the Unit,  
31 after notice to the responsible party has been provided and a reasonable time to correct,  
32 consistent with the conditions, has elapsed, if (a) the Customer has failed to make available  
33 records of verification tests and maintenance of his protective devices; (b) the Unit system  
34 | interferes with UtilityCompany equipment or equipment belonging to other customers of the  
35 | UtilityCompany; (c) the Unit adversely affects the quality of service of adjoining customers.

36  
37 **4.3 Disconnection by Customer:** The Customer may disconnect the Unit at any time.

38  
39 **4.4 Utility Obligation to Cure Adverse Effect:** If, after the Customer meets all  
40 interconnection requirements, the operations of the UtilityCompany are adversely affecting  
41 the performance of the Unit or the Customer's premises, the UtilityCompany shall  
42 immediately take appropriate action to eliminate the adverse effect. If the UtilityCompany  
43 determines that it needs to upgrade or reconfigure its system the Customer will not be

1 responsible for the cost of new or additional equipment beyond the point of common  
2 | coupling between the Customer and the UtilityCompany.

## 3 4 **V. ACCESS**

5  
6 | **5.1 Access to Premises:** The UtilityCompany shall have access to the disconnect  
7 switch of the Unit at all times. At reasonable hours and upon reasonable notice consistent  
8 with Section III of this Agreement, or at any time without notice in the event of an  
9 | emergency (as defined in paragraph 4.1), the UtilityCompany shall have access to the  
10 Premises.

11  
12 | **5.2 UtilityCompany and Customer Representatives:** The UtilityCompany shall  
13 designate, and shall provide to the Customer, the name and telephone number of a  
14 representative or representatives who can be reached at all times to allow the Customer to  
15 | report an emergency and obtain the assistance of the UtilityCompany. For the purpose of  
16 allowing access to the premises, the Customer shall provide the UtilityCompany with the  
17 name and telephone number of a person who is responsible for providing access to the  
18 Premises.

19  
20 | **5.3 UtilityCompany Right to Access UtilityCompany-Owned Facilities and  
21 Equipment:** If necessary for the purposes of this Agreement, the Customer shall allow the  
22 | UtilityCompany access to the Utility'sCompany's equipment and facilities located on the  
23 Premises. To the extent that the Customer does not own all or any part of the property on  
24 | which the UtilityCompany is required to locate its equipment or facilities to serve the  
25 Customer under this Agreement, the Customer shall secure and provide in favor of the  
26 | UtilityCompany the necessary rights to obtain access to such equipment or facilities,  
27 including easements if the circumstances so require.

## 28 29 **VI. DISPUTE RESOLUTION**

30  
31 | **6.1 Good Faith Resolution of Disputes:** Each Party agrees to attempt to resolve all  
32 disputes arising hereunder promptly, equitably and in a good faith manner.

33  
34 | **6.2 Mediation:** If a dispute arises under this Agreement, and if it cannot be resolved by  
35 the Parties within ten (10) business days after written notice of the dispute, the parties agree  
36 to submit the dispute to mediation by a mutually acceptable mediator, in a mutually  
37 convenient location in New York State, in accordance with the then current CPR Institute  
38 for Dispute Resolution Mediation Procedure, or to mediation by a mediator provided by the  
39 New York Public Service Commission. The Parties agree to participate in good faith in the  
40 mediation for a period of up to 90 days. If the Parties are not successful in resolving their  
41 disputes through mediation, then the parties may refer the dispute for resolution to the  
42 New York Public Service Commission, which shall maintain continuing jurisdiction over  
43 | this Agreementagreement.

1  
2 **6.3 Escrow:** If there are amounts in dispute of more than two thousand dollars (\$2,000),  
3 the Customer shall either place such disputed amounts into an independent escrow account  
4 pending final resolution of the dispute in question, or provide to the UtilityCompany an  
5 appropriate irrevocable standby letter of credit in lieu thereof.  
6

7 **VII. INSURANCE**  
8

9 **7.1** The Customer is not required to provide general liability insurance coverage as part  
10 of this Agreement, the SIR, or any other UtilityCompany requirement. Due to the risk of  
11 incurring damages however, the Public Service Commission recommends that every  
12 distributed generation customer protect itself with insurance.  
13

14 **7.2 Effect:** The inability of the UtilityCompany to require the Customer to provide  
15 general liability insurance coverage for operation of the Unit is not a waiver of any rights  
16 the UtilityCompany may have to pursue remedies at law against the Customer to recover  
17 damages.  
18

19 **VIII. MISCELLANEOUS PROVISIONS**  
20

21 **8.1 Beneficiaries:** This Agreement is intended solely for the benefit of the  
22 Partiesparties hereto, and if a Partyparty is an agent, its principal. Nothing in this  
23 Agreement shall be construed to create any duty to, or standard of care with reference to, or  
24 any liability to, any other person.  
25

26 **8.2 Severability:** If any provision or portion of this Agreement shall for any reason be  
27 held or adjudged to be invalid or illegal or unenforceable by any court of competent  
28 jurisdiction, such portion or provision shall be deemed separate and independent, and the  
29 remainder of this Agreement shall remain in full force and effect.  
30

31 **8.3 Entire Agreement:** This Agreement constitutes the entire Agreement between the  
32 Partiesparties and supersedes all prior agreements or understandings, whether verbal or  
33 written.  
34

35 **8.4 Waiver:** No delay or omission in the exercise of any right under this Agreement  
36 shall impair any such right or shall be taken, construed or considered as a waiver or  
37 relinquishment thereof, but any such right may be exercised from time to time and as often  
38 as may be deemed expedient. In the event that any agreement or covenant herein shall be  
39 breached and thereafter waived, such waiver shall be limited to the particular breach so  
40 waived and shall not be deemed to waive any other breach hereunder.  
41

42 **8.5 Applicable Law:** This Agreement shall be governed by and construed in  
43 accordance with the law of the State of New York.

1  
2 **8.6 Amendments:** This Agreement shall not be amended unless the amendment is in  
3 writing and signed by the UtilityCompany and the Customer.  
4

5 **8.7 Force Majeure:** For purposes of this Agreement, "Force Majeure Event" means  
6 any event: (a) that is beyond the reasonable control of the affected Party; and (b) that the  
7 affected Party is unable to prevent or provide against by exercising reasonable diligence,  
8 including the following events or circumstances, but only to the extent they satisfy the  
9 preceding requirements: acts of war, public disorder, insurrection, or rebellion; floods,  
10 hurricanes, earthquakes, lightning, storms, and other natural calamities; explosions or fires;  
11 strikes, work stoppages, or labor disputes; embargoes; and sabotage. If a Force Majeure  
12 Event prevents a Party from fulfilling any obligations under this Agreement, such Party will  
13 promptly notify the other Party in writing, and will keep the other Party informed on a  
14 continuing basis of the scope and duration of the Force Majeure Event. The affected Party  
15 will specify in reasonable detail the circumstances of the Force Majeure Event, its expected  
16 duration, and the steps that the affected Party is taking to mitigate the effects of the event on  
17 its performance. The affected Party will be entitled to suspend or modify its performance of  
18 obligations under this Agreement, other than the obligation to make payments then due or  
19 becoming due under this Agreement, but only to the extent that the effect of the Force  
20 Majeure Event cannot be mitigated by the use of reasonable efforts. The affected Party will  
21 use reasonable efforts to resume its performance as soon as possible.  
22

23 **8.8 Assignment to Corporate Party:** At any time during the term, the Customer may  
24 assign this Agreement to a corporation or other entity with limited liability, provided that the  
25 Customer obtains the consent of the UtilityCompany. Such consent will not be withheld  
26 unless the UtilityCompany can demonstrate that the corporate entity is not reasonably  
27 capable of performing the obligations of the assigning Customer under this Agreement.  
28

29 **8.9 Assignment to Individuals:** At any time during the term, ~~the~~ Customer may  
30 assign this Agreement to another person, other than a corporation or other entity with  
31 limited liability, provided that the assignee is the owner, lessee, or is otherwise responsible  
32 for the Unit.  
33

34 **8.10 Permits and Approvals:** Customer shall obtain all environmental and other  
35 permits lawfully required by governmental authorities prior to the construction and for the  
36 operation of the Unit during the term of this Agreement.  
37

38 **8.11 Limitation of Liability:** Neither by inspection, if any, or non-rejection, nor in any  
39 other way, does the UtilityCompany give any warranty, express or implied, as to the  
40 adequacy, safety, or other characteristics of any structures, equipment, wires, appliances or  
41 devices owned, installed or maintained by the Customer or leased by the Customer from  
42 third parties, including without limitation the Unit and any structures, equipment, wires,  
43 appliances or devices appurtenant thereto.

1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21

**ACCEPTED AND AGREED:**

**Customer Signature:** \_\_\_\_\_

**Printed Name:** \_\_\_\_\_

**Title:** \_\_\_\_\_

**Date:** \_\_\_\_\_

**Utility Signature:** \_\_\_\_\_

**Printed Name:** \_\_\_\_\_

**Title:** \_\_\_\_\_

**Company:** \_\_\_\_\_

**Date:** \_\_\_\_\_

1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52

**APPENDIX B**

**NEW YORK STATE STANDARDIZED APPLICATION  
FOR ~~SINGLE PHASE~~ ATTACHMENT OF INVERTER BASED PARALLEL  
GENERATION EQUIPMENT 25 KW OR LESS  
TO THE ELECTRIC SYSTEM OF**

**Utility:** \_\_\_\_\_

**Customer:**

Name: \_\_\_\_\_ Phone: (\_\_\_\_) \_\_\_\_\_

Fax: (\_\_\_\_) \_\_\_\_\_

Email: \_\_\_\_\_

Address: \_\_\_\_\_ Municipality: \_\_\_\_\_

Utility Account Number: \_\_\_\_\_ Utility Meter No.: \_\_\_\_\_

**Agent (if any):**

Name: \_\_\_\_\_ Phone: (\_\_\_\_) \_\_\_\_\_

Fax: (\_\_\_\_) \_\_\_\_\_

Email: \_\_\_\_\_

Address: \_\_\_\_\_ Municipality: \_\_\_\_\_

**Consulting Engineer or Contractor:**

Name: \_\_\_\_\_ Phone: (\_\_\_\_) \_\_\_\_\_

Email: \_\_\_\_\_

Fax: (\_\_\_\_) \_\_\_\_\_

Address: \_\_\_\_\_  
\_\_\_\_\_

**Estimated In-Service Date:** \_\_\_\_\_

**Existing Electric Service:**

Capacity: \_\_\_\_\_ Amperes Voltage: \_\_\_\_\_ Volts

Service Character: ( )Single Phase ( )Three Phase

**Location of Protective Interface Equipment on Property:**

(include address if different from customer address)

\_\_\_\_\_

1  
2  
3  
4  
5  
6 **Energy Producing Equipment/Inverter Information:**

7  
8 **Total AC Nameplate Rating of All Inverters:**

9  
10 Inverter

11 \_\_\_\_\_  
12  
13 Inverter or Manufacturer: \_\_\_\_\_  
14 Model No. \_\_\_\_\_ Version No. \_\_\_\_\_  
15 ( ) Synchronous ( ) Induction ( ) Inverter ( ) Other \_\_\_\_\_  
16 Rating: \_\_\_\_\_ kW Rating: \_\_\_\_\_ kVA  
17 Generator Connection: ( ) Delta ( ) Wye ( ) Wye Grounded  
18 Interconnection Voltage: \_\_\_\_\_ Volts  
19 System Type Tested to UL 1741 ( most Current version)  
20 (Total System): ( ) Yes ( ) No; attach product literature

21  
22 Manufacturer: \_\_\_\_\_ Model: \_\_\_\_\_  
23 Quantity: \_\_\_\_\_  
24 Rating per inverter: \_\_\_\_\_ kW  
25 Type: ( ) Forced Commutated ( ) Line Commutated  
26 Rated Output: \_\_\_\_\_ Amps \_\_\_\_\_ Volts  
27 Ramp Rate: \_\_\_\_\_  
28 Method of Grounding ( ) Grounded ( ) Ungrounded  
29 Quantity of Inverters \_\_\_\_\_

30  
31 If there is more than one inverter of different types or manufacturers please provide information on separate  
32 sheet.

33  
34 If Applicable:

35  
36 Step Up Transformer Winding Configuration: Wye-Wye ( ) Wye-Delta ( ) Delta – Wye ( )

37  
38 Other existing DG such as stand-by emergency generators, other renewable technologies, microturbines,  
39 hydro, fuel cells, battery storage, etc. ( ) Yes ( ) No.

40  
41 If Yes provide information about existing generation on separate sheet and include detail on one-line  
42 diagram.

43  
44  
45 Equipment Type Tested (i.e. Inverter, Protection System):  
46 ( ) Yes ( ) No; attach product literature  
47 Three line Diagram attached: ( ) Yes  
48 Installation Test Plan attached: ( ) Yes  
49 If applicable, Certification to UL 1741 attached: ( ) Yes

50 **Signature:**

51



1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52



APPENDIX C

NEW YORK STATE STANDARDIZED APPLICATION  
FOR ATTACHMENT OF **NON-INVERTER BASED** PARALLEL GENERATION  
EQUIPMENT **ABOVE 25 KW UP TO 2 MW**  
TO THE ELECTRIC SYSTEM OF

Utility: \_\_\_\_\_

Customer:  
Name: \_\_\_\_\_ Phone: (\_\_\_\_) \_\_\_\_\_

1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38

Fax: (\_\_\_\_)\_\_\_\_\_

Email: \_\_\_\_\_

Address: \_\_\_\_\_ Municipality: \_\_\_\_\_

Utility Account Number: \_\_\_\_\_ Utility Meter No.: \_\_\_\_\_

**Agent (if any):**

Name: \_\_\_\_\_ Phone: (\_\_\_\_)\_\_\_\_\_

Fax: (\_\_\_\_)\_\_\_\_\_

Email: \_\_\_\_\_

Address: \_\_\_\_\_ Municipality: \_\_\_\_\_

**Consulting Engineer or Contractor:**

Name: \_\_\_\_\_ Phone: (\_\_\_\_)\_\_\_\_\_

Address: \_\_\_\_\_

\_\_\_\_\_

**Estimated In-Service Date:** \_\_\_\_\_

**Existing Electric Service:**

Capacity: \_\_\_\_\_ Amperes Voltage: \_\_\_\_\_ Volts

Service Character: ( )Single Phase ( )Three Phase

Secondary 3 Phase Transformer Connection ( )Wye ( )Delta

**Location of Protective Interface Equipment on Property:**

(include address if different from customer address)

\_\_\_\_\_

1 | **Energy Producing Equipment/~~Inverter~~ Information:**

2 | Manufacturer: \_\_\_\_\_  
3 | Model No. \_\_\_\_\_ Version No. \_\_\_\_\_  
4 | ( ) Synchronous ( ) Induction ( ) ~~Inverter~~ (  ) Other \_\_\_\_\_  
5 | Rating: \_\_\_\_\_ kW Rating: \_\_\_\_\_ kVA  
6 | Rated Output: \_\_\_\_\_ VA Rated Voltage: \_\_\_\_\_ Volts  
7 | Rate Frequency: \_\_\_\_\_ Hertz Rated Speed: \_\_\_\_\_ RPM  
8 | Efficiency: \_\_\_\_\_ % Power Factor: \_\_\_\_\_ %  
9 | Rated Current: \_\_\_\_\_ Amps Locked Rotor Current: \_\_\_\_\_ Amps  
10 | Synchronous Speed: \_\_\_\_\_ RPM Winding Connection:  
11 | Min. Operating Freq./Time:  
12 | Generator Connection: ( ) Delta ( ) Wye ( ) Wye Grounded  
13 | System ~~Type~~-Tested to UL 1741 (most Current version) (Total System): ( ) Yes ( ) No; attach  
14 | product \_\_\_\_\_ literature  
15 | \_\_\_\_\_ literature  
16 | Equipment ~~Type~~-Tested to UL 1741 (most Current version) (i.e. ~~Inverter~~, Protection System):  
17 | ( ) Yes ( ) No; attach product literature  
18 | Three line Diagram attached: ( ) Yes  
19 | Verification Test Plan attached: ( ) Yes  
20 | If applicable, Certification to UL 1741 attached: ( ) Yes

21 |  
22 | **For Synchronous Machines:**

23 | Submit copies of the Saturation Curve and the Vee Curve  
24 | ( ) Salient ( ) Non-Salient  
25 | Torque: \_\_\_\_\_ lb-ft Rated RPM: \_\_\_\_\_  
26 | Field Amperes: \_\_\_\_\_ at rated generator voltage and current  
27 | and \_\_\_\_\_ % PF over-excited  
28 | Type of Exciter: \_\_\_\_\_  
29 | Output Power of Exciter: \_\_\_\_\_  
30 | Type of Voltage Regulator: \_\_\_\_\_  
31 | Direct-axis Synchronous Reactance ( $X_d$ ) \_\_\_\_\_ ohms  
32 | Direct-axis Transient Reactance ( $X'_d$ ) \_\_\_\_\_ ohms  
33 | Direct-axis Sub-transient Reactance ( $X''_d$ ) \_\_\_\_\_ ohms

34 |  
35 | **For Induction Machines:**

36 | Rotor Resistance ( $R_r$ ) \_\_\_\_\_ ohms Exciting Current \_\_\_\_\_ Amps  
37 | Rotor Reactance ( $X_r$ ) \_\_\_\_\_ ohms Reactive Power Required:  
38 | Magnetizing Reactance ( $X_m$ ) \_\_\_\_\_ ohms \_\_\_\_\_ VARs (No Load)  
39 | Stator Resistance ( $R_s$ ) \_\_\_\_\_ ohms \_\_\_\_\_ VARs (Full Load)  
40 | Stator Reactance ( $X_s$ ) \_\_\_\_\_ ohms  
41 | Short Circuit Reactance ( $X''_d$ ) \_\_\_\_\_ ohms Phases:  
42 | Frame Size: \_\_\_\_\_ Design Letter: \_\_\_\_\_ ( ) Single  
43 | Temp. Rise: \_\_\_\_\_ °C. ( ) Three-Phase

44 |  
45 | If Applicable:

46 |  
47 | Step Up Transformer Winding Configuration: Wye-Wye ( ) Wye-Delta ( ) Delta – Wye ( )

48 |  
49 | **For Inverters:**

50 | ~~\_\_\_\_\_~~ Manufacturer: \_\_\_\_\_ Model: \_\_\_\_\_  
51 | ~~\_\_\_\_\_~~ Type: \_\_\_\_\_ ( ) Forced Commutated ( ) Line Commutated  
52 | ~~\_\_\_\_\_~~ Rated Output: \_\_\_\_\_ Amps \_\_\_\_\_ Volts

1 | \_\_\_\_\_ Efficiency: \_\_\_\_\_%

2 |

3 | **Signature:**

4 |

5 |

6 | \_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

7 | \_\_\_\_\_

8 | CUSTOMER/AGENT SIGNATURE

\_\_\_\_\_ TITLE

9 | DATE

10 |

1  
2  
3  
4  
5

APPENDIX D

COST RESPONSIBILITY FOR DEDICATED TRANSFORMER(S) AND OTHER SAFETY EQUIPMENT

<u>Generator Type</u>	<u>Generator Size</u>	<u>Equipment Cost to Residential Customers</u>	<u>Equipment Cost to Non-Residential Customers</u>
<u>Micro-CHP</u>	<u>Less than or equal to 10 kW</u>	<u>\$350 maximum</u>	<u>N/A</u>
<u>Fuel Cell</u>	<u>Less than or equal to 10 kW</u>	<u>\$350 maximum</u>	<u>As determined by Utility*</u>
<u>Fuel Cell</u>	<u>Over 10 kW up to 1.5 MW</u>	<u>N/A</u>	<u>As determined by Utility*</u>
<u>Solar</u>	<u>Less than or equal to 25 kW</u>	<u>\$350 maximum</u>	<u>\$350 maximum</u>
<u>Solar</u>	<u>Over 25 kW up to 2 MW</u>	<u>N/A</u>	<u>As determined by Utility*</u>
<u>Micro-hydroelectric</u>	<u>Less than or equal to 25 kW</u>	<u>\$350 maximum</u>	<u>As determined by Utility*</u>
<u>Micro-hydroelectric</u>	<u>Over 25 kW up to 2 MW</u>	<u>N/A</u>	<u>As determined by Utility*</u>
<u>Wind **</u>	<u>Less than or equal to 25 kW</u>	<u>\$750 maximum</u>	<u>\$750 maximum</u>
<u>Wind</u>	<u>Over 25 kW up to 2 MW</u>	<u>N/A</u>	<u>As determined by Utility*</u>
<u>Farm Wind **</u>	<u>Over 25 kW up to 500 kW</u>	<u>N/A</u>	<u>\$5,000 maximum</u>
<u>Farm Waste **</u>	<u>Up to 1 MW</u>	<u>N/A</u>	<u>\$5,000 maximum</u>

6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24

\* Subject to review by the Commission at the request of the Customer. Such costs can include the total costs for upgrades to ensure the adequacy of the distribution system which would not have been necessary but for the interconnection of the net metered DG resource (as per PSL §66-j(3)(c)(iii) or PSL §66-l(3)(c)(iii)).

\*\* Residential and Non-Residential Wind Customers with a total rated capacity up to 25 kW, Farm Wind and Farm Waste Customers may be required to also pay for feeder line upgrades that would not be required but for the interconnection of the net metered DG resource. Residential and Non-Residential Wind, Farm Wind and Farm Waste Customers are responsible for all feeder line upgrade costs if the total nameplate rating of the generating equipment exceeds 20% of the rated capacity of the feeder line (as per PSL §66-l(5)(c)(ii) and PSL §66-j(5)(b)(iii)). Farm Wind Customers are responsible for 50% of feeder line upgrade costs if the total nameplate rating of the generating equipment does not exceed 20% of the rated capacity of the feeder line(as per PSL §66-l(2)).